

RIPCORD

Ripcord Alarm

If the lanyard is detached from the device a 10-second pre-warning alarm beeps before an alarm is raised to the ARC.

To cancel this alarm, re-insert the lanyard loop piece back into the device before the audio beeps stop.

LED SCREEN

View the remaining battery, GPS signal, network, mobile strength, time and unique IMEI number with a **single press** of the **power button**. The LED screen will display for a few seconds before entering sleep mode to conserve battery.

CALL BUTTON

Check In/Out

Press and hold for 3 seconds. Allows users to Check In safely at the start of their day. **Press and hold** again to Check Out at the end of the day to confirm your safety.

SOS BUTTON

SOS Alarm

Press and hold for 4 seconds. The device will vibrate and connect to the ARC. If you activate the alarm by mistake, inform the controller by stating "False alarm".

Test Line

Double press and leave a message. Listen to the message playback to check the sound quality.




POWER BUTTON

Power On/Off

Press and hold for 4 seconds to turn on/off. The LED screen will state Power Off before the device turns off.

Manual Position

Press and hold for 2 seconds. The LED screen will state Manual Position when your GPS location has been sent to Peoplesafe.



CHECK IN/OUT

At the start of your working day or before commencing a task, Check In so **managers** can see you have started work safely. When the task has finished or at the end of your working day, Check Out to confirm your safety.

To activate: Press and hold the call button for 3 seconds.



TEST LINE

Have confidence that the device will work when you need it most. Perform a test call to ensure the device is registered and check the sound quality. We recommend completing this test every three months.

To activate: Double press the call button.

USEFUL NUMBERS

Save the Peoplesafe ARC phone numbers to your contact list on your smartphone.

+44203 750 0998

+44208 786 1010

For more information download the user guide from our Help Centre.



ID140-TL-CK-HTGO1